

MARUSON[®]

AVR SYSTEMS

LOGIC AVR-1000VA,1200VA,2200VA

Applications: Home Entertainment Systems, Televisions, Personal Computers, Printers, Faxes, Copiers, Laptop, Network Peripherals, and Many Other Electronic Equipment

AVR-1000A, 1200A, 2200A

Features:

- Desk Top and Wall Mountable Design
- Internet , ADSL , Tel/Fax Data Line Surge Protection
- Automatically Regulating High Voltage and Low Voltage
- 6 Outlets for 1000VA (4 AVR & Surge + 2 Surge)
- 10 Outlets for 1200VA/2200VA (5 AVR & Surge + 5 Surge)
- Over Heating Protection
- Visual Indicators of AVR Functions
- Resetable Overload Protection by Circuit Breaker



Specification:

Model		AVR-1000A	AVR-1200A	AVR-2200A
Capacity		1000VA/500W	1200VA/600W	2200VA/1100W
AC Input	Nominal Voltage	120VAC / 230VAC		
	Input Voltage Range	95VAC ~ 150VAC / 176VAC ~ 287VAC		
	Phase	1 Phase 2 Wires		
	Frequency	50/60Hz (auto sensing)		
AC Output	Output Voltage Range	108VAC ~ 129VAC / 205VAC ~ 246VAC		
	Frequency	50 or 60Hz		
Outlets	Nema 5-15R	6 Outlets	10 Outlets	
Protection	Surge Suppression	84 Joules	110 Joules	
	Network Surge Suppression	RJ-11	RJ-11/RJ-45	
	Overload	Manual Reset Circuit Switch		
	Short Circuit	Manual Reset Circuit Switch		
LED	Power On/Off	Green LED		
	Regulate	Yellow LED		
Environment	Operating Temperature	0 ~ 40 °C / 32 ~ 104 °F		
	Relative Humidity	0 ~ 95%, non-condensing		
	Audible Noise	< 40 dB at 1meter		
Physical	Dimension(W*H*D) in./mm	7.9*5.5*2.75 in. / 200*140*70 mm	8.94*6.3*3.07 in. / 227*160*78 mm	
	Net Weight	3.3lbs / 1.49kg	3.64lbs / 1.65kg	5.07lbs / 2.3kg
Warranty		3 years limited		

*Specifications may change at any time without notice.

*All trade marks belong to their respected owners.

Automatic Voltage Regulator